How to update of IF-NMEASC

Preparation

Connect a PC to IF-NMEASC with a USB cable

<u>Necessary tool</u> (a) A USB cable

(b)Program files for ver. 2051523-02.01

Procedure

- 1. Check the COM port No. during connecting PC to IF-NMEASC .
 - 1) Click the right button of mouse on my computer on PC.
 - 2) Execute "Device manager".
 - 3) Open the Ports (COM&LPT) tree.
 - 4) Check the COM port No of IF-NMEASC.

📮 Device Manager	
<u>File Action View H</u> elp	
E	_
🗄 😼 Computer	
🕀 🖘 Disk drives	
🗄 😼 Display adapters	
🕀 🥝 DVD/CD-ROM drives	
🔄 📹 Floppy disk controllers	
🗄 🤳 Floppy disk drives	
🗄 📹 IDE ATA/ATAPI controllers	
🗄 🦢 Keyboards	
🗄 🕥 Mice and other pointing devices	
🗄 🧐 Monitors	
🔁 🖷 Network adapters	
🖨 🖉 Ports (COM & LPT)	
- 🖉 Communications Port (COM1)	
— 💹 ECP Printer Port (LPT1)	
IF-NMEASC (COM3) 🚽	
🔁 🛲 Processors	
🔃 🧐 Sound, video and game controllers	
🖶 😼 System devices	
🕀 🖨 Universal Serial Bus controllers	_

 Open the update.batof program files and then edit the below yellow word to the COM port of IF-NMEASC.

up gcc usb<mark>3</mark>

- 3. Execute update.bat and then start updating.
- 4. Check the software version with SC-30 tool.

lost Name	Unique ID	Name TE-NMEASC	2051523-02.01	ion
ŎM6	1855-4-0006603-0.00-00	SC-30	2051522-01.07	Ver1
		Success		
		OK		
]